

What are the differences between the GeoExplorer 2001, 2003 and 2005 Series?

Part numbers in **bold** occur on the San Juan NF.

NOTE: Accessories (like the serial clip) are not interchangeable between the *pre-2005* and *2005* series.

GeoExplorer 2005 series



Part Numbers
 60950-00 (XH)
60950-20 (XT)
 60950-50 (XM)

- USB hub **not recommended** for support module connection to PC to avoid communication problems.
- Operating System is Windows Mobile 2005 (version 5 or greater).
- Bluetooth capable
- 2005 series support module.
- 2005 series serial clip.
- TFT (Thin Film Transistor) screen
- 64MB RAM
- 512MB on board Flash disk space.
- SD memory expansion card slot.

GeoExplorer 2003 series (discontinued)



Part Numbers
CE.NET
49050-20 (XT)
 49050-30 (XT)
49050-50 (XM)
 49050-60 (XT)
 49050-70 (XT)
 49050-75 (XT)

Windows Mobile
50950-20 (XT)
50950-50 (XM)
 49050-70 (XT)
 49050-75 (XT)

- USB hub **required** for support module connection to PC with USB 2.0 to prevent computer damage.
- Operating System is either
 - Windows CE.NET (version 2.00.02)
 - Windows Mobile 2003 (version 3.00.01)
- Bluetooth capable.
- pre-2005 series support module.
- pre-2005 series serial clip.
- TFT (Thin Film Transistor) screen
- 64MB RAM main memory.
- 512MB on board Flash disk space.
- No expansion memory slot.

GeoExplorer 2001 series (discontinued)



Part Numbers
 46475-00, 46475-10 (XT) 128 MB
 46475-20, 46475-30, 46475-60, 46475-70, 46475-75 (XT) 512 MB
 46475-50 (XM) 512 MB

- USB hub **required** for support module connection to PC with USB 2.0 to prevent computer damage.
- Operating System is either
 - Windows CE 3.0 (version 1.10.02 or earlier)
 - Windows CE.NET (version 2.00.02)
- No Bluetooth capability.
- pre-2005 series support module.
- pre-2005 series serial clip.
- Non-TFT screen
- 32MB RAM
- 128MB or 512MB Flash disk space.
- No expansion memory slot.